

**Cover frame and E22 device box for flat mounting
1-gang**



Specification	Order No.	Packing unit	PS	EAN
 Stainless Steel	2881 202	1	11	4010337049647
 Aluminium	2881 203	1	11	4010337049654
 pure white glossy (thermoplastic)	2881 201	1	01	4010337049630

Information

The Gira E22 switch range offers a new method for mounting. Using a special device box, it can be installed flat on the wall. This E22 device box can be installed directly in the wall in cases of hollow-wall mounting, e.g. a flexible wall system. For flush-mounting in masonry, the E22 device box is inserted in an E22 flush-mounted box, which is then placed in the wall.

Installation in hollow wall:

- Produce rectangular cut-out (template included).
- Mount and align E22 device box and screw in with claws (mounting as with a market-standard hollow wall box).
- Install devices and cover frames in usual manner. The device box has no cable retainer.

Installation in masonry:

- Product rectangular cut-out (e.g. with a keyway cutter/caulking hammer, angular bit/caulking hammer, chisel).
- Install and align E22 flush-mounted box **2891 00, 2892 00, 2893 00, 2894 00** and, for example, secure with plaster.
- Mount plaster protection (included with E22 flush-mounted box).
- Plaster the wall.
- Remove the plaster protection and cut the opening clear.
- Mount and align E22 device box and screw in with claws (mounting as with a market-standard hollow wall box).
- Install devices and cover frames in usual manner. The device box has no cable retainer.