



Main

For independent switching of four loads via make contacts. With integrated bus coupler 2 and screw terminals. For installation on DIN rails EN 50022. The 230 V switch output can be operated with a manual switch.

Complementary

The bus is connected using a bus connecting terminal; a data rail is not necessary. A green LED indicates readiness for operation after the application has been loaded.

KNX software functions:

Operation as break or make contact, delay functions for each channel, staircase lighting function with/without manual OFF function, cut-out warning for staircase lighting function, blocking and additional logic operation or priority control, scenes, status feedback function per channel, central function, comprehensive parameterisation for bus voltage failure and recovery, parameterisable download behaviour.

Nominal voltage: AC 230 V, 50-60 Hz

For each switching contact:

Nominal current: 16 A, $\cos\varphi = 0,6$

Incandescent lamps: AC 230 V, max. 3600 W

Halogen lamps: AC 230 V, max. 2500 W

Fluorescent lamps: AC 230 V, max. 2500 VA

Capacitive load: AC 230 V, 16 A, max. 200 μF

Device width: 4 modules = approx. 72 mm

Contents: With bus connecting terminal and cable cover.

Colour: light grey